

AVR202: 16-bit Arithmetics

Features

- Easily Expandable to 32-bit or Any Word Length
- Code Density and Speed Matches 16-bit Controllers
- Runnable Example Program

Introduction

This application note lists program examples for arithmetic operation on 16-bit values. A listing of all implementations with key performance specifications is given in Table 1.

Table 1. Performance Figures Summary

Application	Code Size (Words)	Execution Time (Cycles)
Add two 16-bit register variables	2	2
Add 16-bit immediate to 16-bit register variable	2	2
Subtract two 16-bit register variables	2	2
Subtract 16-bit immediate from 16-bit reg. variable	2	2
Compare two 16-bit register variables	2	2
Compare 16-bit immediate to 16-bit reg. variable	3	3
Negate a 16-bit register variable	4	4

16 + 16-bit Register Addition

This operation is done as follows:

1. Add Low bytes.
2. Add with carry High bytes.

By adding more Add with Carry instructions, numbers of n -byte width can be added using n instructions.

16-bit Register + 16-bit Immediate Addition

As the AVR has no add immediate or add immediate with carry, the subtract immediate and subtract immediate with carry instructions are used. The operation is done as follows:

1. Subtract immediate Low byte of negated number from register Low byte.
2. Subtract immediate with carry High byte of negated number from register High byte.

By adding more Add with Carry instructions, numbers of n -byte width can be added using n instructions.



8-bit **AVR**[®]
Microcontroller

Application
Note

Rev. 0937B-AVR-05/02



16 – 16-bit Register Subtraction

This operation is done as follows:

1. Subtract Low bytes.
2. Subtract with carry high Bytes.

By adding more Subtract with Carry instructions, numbers of n -byte width can be subtracted using n instructions.

16-bit Register + 16-bit Immediate Subtraction

This operation is done as follows:

1. Subtract immediate Low byte from register Low byte.
2. Subtract with carry immediate High byte from register High byte.

By adding more Subtract with Carry instructions, numbers of n -byte width can be subtracted using n instructions.

Compare Two 16-bit Register Variables

This operation is done as follows:

1. Compare Low bytes.
2. Compare with carry High bytes.

Note that the Compare with Carry instruction supports zero-propagation, which means that all conditional branch instructions can be used following the two-step compare operation. By adding more Compare with Carry instructions, numbers of n -byte width can be compared using n instructions.

Compare a 16-bit Register with a 16-bit Immediate

This operation is done as follows:

1. Compare register Low byte to immediate Low byte.
2. Store immediate High byte to a third register.
3. Compare with carry High bytes.

Negate (2's Complement) a 16-bit Register Variable

This operation is done as follows:

1. Invert (1's Complement) Low byte
2. Invert (1's Complement) high byte
3. Subtract \$FF from Low byte.
4. Subtract with carry \$FF from High byte.

Note: Steps 3 and 4 are equivalent to adding \$0001 to the 16-bit number.





Atmel Headquarters

Corporate Headquarters

2325 Orchard Parkway
San Jose, CA 95131
TEL 1(408) 441-0311
FAX 1(408) 487-2600

Europe

Atmel Sarl
Route des Arsenaux 41
Case Postale 80
CH-1705 Fribourg
Switzerland
TEL (41) 26-426-5555
FAX (41) 26-426-5500

Asia

Room 1219
Chinachem Golden Plaza
77 Mody Road Tsimhatsui
East Kowloon
Hong Kong
TEL (852) 2721-9778
FAX (852) 2722-1369

Japan

9F, Tonetsu Shinkawa Bldg.
1-24-8 Shinkawa
Chuo-ku, Tokyo 104-0033
Japan
TEL (81) 3-3523-3551
FAX (81) 3-3523-7581

Atmel Operations

Memory

2325 Orchard Parkway
San Jose, CA 95131
TEL 1(408) 441-0311
FAX 1(408) 436-4314

Microcontrollers

2325 Orchard Parkway
San Jose, CA 95131
TEL 1(408) 441-0311
FAX 1(408) 436-4314

La Chantrerie
BP 70602
44306 Nantes Cedex 3, France
TEL (33) 2-40-18-18-18
FAX (33) 2-40-18-19-60

ASIC/ASSP/Smart Cards

Zone Industrielle
13106 Rousset Cedex, France
TEL (33) 4-42-53-60-00
FAX (33) 4-42-53-60-01

1150 East Cheyenne Mtn. Blvd.
Colorado Springs, CO 80906
TEL 1(719) 576-3300
FAX 1(719) 540-1759

Scottish Enterprise Technology Park
Maxwell Building
East Kilbride G75 0QR, Scotland
TEL (44) 1355-803-000
FAX (44) 1355-242-743

RF/Automotive

Theresienstrasse 2
Postfach 3535
74025 Heilbronn, Germany
TEL (49) 71-31-67-0
FAX (49) 71-31-67-2340

1150 East Cheyenne Mtn. Blvd.
Colorado Springs, CO 80906
TEL 1(719) 576-3300
FAX 1(719) 540-1759

Biometrics/Imaging/Hi-Rel MPU/ High Speed Converters/RF Datacom

Avenue de Rochepleine
BP 123
38521 Saint-Egreve Cedex, France
TEL (33) 4-76-58-30-00
FAX (33) 4-76-58-34-80

e-mail

literature@atmel.com

Web Site

<http://www.atmel.com>

© Atmel Corporation 2002.

Atmel Corporation makes no warranty for the use of its products, other than those expressly contained in the Company's standard warranty which is detailed in Atmel's Terms and Conditions located on the Company's web site. The Company assumes no responsibility for any errors which may appear in this document, reserves the right to change devices or specifications detailed herein at any time without notice, and does not make any commitment to update the information contained herein. No licenses to patents or other intellectual property of Atmel are granted by the Company in connection with the sale of Atmel products, expressly or by implication. Atmel's products are not authorized for use as critical components in life support devices or systems.

ATMEL® and AVR® are the registered trademarks of Atmel.

Other terms and product names may be the trademarks of others.



Printed on recycled paper.